

KVM HDMI 4x1 Quad Multi-viewer

(4K@30Hz)

Data Sheet



Introduction

KVM HDMI 4x1 Quad Multi-viewer is a high performance device with four HD screen segmentation, It supports mouse and keyboard control to switch four way computers. It can display 4 HD digital video signal on the same screen with a variety of video segmentation. The control methods is flexible, it can be switched via button and IR control. It's a very practical and stable multi-viewer and easy to install, it can be used in the major projects, meeting halls and other places.



Features

- Support 4 HDMI inputs, 1 HDMI output ;
- Support 4 channels HDMI signal screen segmentation ;
- Support highest resolution up to 4K@30Hz ;
- Support resolution 4K,1080P,720P,1024X768,1360X768,etc;
- Support IR control ;
- Support audio output format: PCM ;
- Supports 1 way mouse and keyboard to control 4 ways PC host ;
- USB supports Windows/Linux/MAC OS and Android operation system, etc; Plug and play;
- Support USB 1.1 Low speed(1.5Mb/s); Full speed(12Mb/s) ;

Specifications

HDMI resolution	4K/30Hz
Audio format	PCM
Input cable distance	4K/30Hz ≤10M AWG26 HDMI standard cable
Output cable distance	4K/30Hz ≤10M AWG26 HDMI standard cable
Max bandwidth	340MHz
Max baud rate	3.4x3Gbps
Maximum working current	400 mA
Power adapter format	Input AC (50 hz, 60 hz) 100V to 240V; Output: DC 12V 1A
Operating Temperature range	(-10 ~ + 45 °C)
Dimension	256x153x35(mm)
Weight	1.2Kg

8 models for watching



Single screen



Left and right dual picture



Up and down dual picture



picture in picture



Three pictures



one big and three small mode



Four pictures-H



Four pictures